

<b>STN</b>	<b>Svietidlá</b> <b>Časť 1: Všeobecné požiadavky a skúšky</b>	<b>STN</b> <b>EN IEC 60598-1</b>  36 0600
------------	--	--

Luminaires - Part 1: General requirements and tests

Táto norma obsahuje anglickú verziu európskej normy.  
This standard includes the English version of the European Standard.

Táto norma bola oznámená vo Vestníku ÚNMS SR č. 07/21

Obsahuje: EN IEC 60598-1:2021, IEC 60598-1:2020

Oznámením tejto normy sa od 19.03.2024 ruší  
STN EN 60598-1 (36 0600) z augusta 2016

**133140**



EUROPEAN STANDARD

**EN IEC 60598-1**

NORME EUROPÉENNE

EUROPÄISCHE NORM

March 2021

ICS 29.140.40

Supersedes EN 60598-1:2015 and all of its amendments  
and corrigenda (if any)

English Version

**Luminaires - Part 1: General requirements and tests  
(IEC 60598-1:2020)**Luminaires - Partie 1: Exigences générales et essais  
(IEC 60598-1:2020)Leuchten - Teil 1: Allgemeine Anforderungen und  
Prüfungen  
(IEC 60598-1:2020)

This European Standard was approved by CENELEC on 2020-09-21. CENELEC members are bound to comply with the CEN/CENELEC Internal Regulations which stipulate the conditions for giving this European Standard the status of a national standard without any alteration.

Up-to-date lists and bibliographical references concerning such national standards may be obtained on application to the CEN-CENELEC Management Centre or to any CENELEC member.

This European Standard exists in three official versions (English, French, German). A version in any other language made by translation under the responsibility of a CENELEC member into its own language and notified to the CEN-CENELEC Management Centre has the same status as the official versions.

CENELEC members are the national electrotechnical committees of Austria, Belgium, Bulgaria, Croatia, Cyprus, the Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Iceland, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, the Netherlands, Norway, Poland, Portugal, Republic of North Macedonia, Romania, Serbia, Slovakia, Slovenia, Spain, Sweden, Switzerland, Turkey and the United Kingdom.



European Committee for Electrotechnical Standardization  
Comité Européen de Normalisation Electrotechnique  
Europäisches Komitee für Elektrotechnische Normung

**CEN-CENELEC Management Centre: Rue de la Science 23, B-1040 Brussels**

**EN IEC 60598-1:2021 (E)****European foreword**

The text of document 34D/1546/FDIS, future edition 9 of IEC 60598-1, prepared by SC 34D "Luminaires" of IEC/TC 34 "Lighting" was submitted to the IEC-CENELEC parallel vote and approved by CENELEC as EN IEC 60598-1:2021.

The following dates are fixed:

- latest date by which the document has to be implemented at national (dop) 2021-09-19 level by publication of an identical national standard or by endorsement
- latest date by which the national standards conflicting with the (dow) 2024-03-19 document have to be withdrawn

This document supersedes EN 60598-1:2015 and all of its amendments and corrigenda (if any).

Attention is drawn to the possibility that some of the elements of this document may be the subject of patent rights. CENELEC shall not be held responsible for identifying any or all such patent rights.

This document has been prepared under a mandate given to CENELEC by the European Commission and the European Free Trade Association, and supports essential requirements of EU Directive(s).

For the relationship with EU Directive(s) see informative Annex ZZ, which is an integral part of this document.

**Endorsement notice**

The text of the International Standard IEC 60598-1:2020 was approved by CENELEC as a European Standard without any modification.

In the official version, for Bibliography, the following notes have to be added for the standards indicated:

IEC 60079 (series)	NOTE	Harmonized as EN IEC 60079-7:2015/A1 (series)
IEC 60081	NOTE	Harmonized as EN 60081
IEC 60216 (series)	NOTE	Harmonized as EN 60216 (series)
IEC 60228:2004	NOTE	Harmonized as EN 60228:2005 (not modified)
IEC 60269 (series)	NOTE	Harmonized as EN 60269 (series)
IEC 60357	NOTE	Harmonized as EN 60357
IEC 60364 (series)	NOTE	Harmonized as HD 60364 (series)
IEC 60364-4-41:2005	NOTE	Harmonized as HD 60364-4-41:2017
IEC 60364-5-51	NOTE	Harmonized as HD 60364-5-51
IEC 60364-7-701	NOTE	Harmonized as HD 60364-7-701
IEC 60364-7-702	NOTE	Harmonized as HD 60364-7-702
IEC 60400	NOTE	Harmonized as EN 60400

IEC 60432-3	NOTE	Harmonized as EN 60432-3
IEC 60598-2-3	NOTE	Harmonized as EN 60598-2-3
IEC 60598-2-5	NOTE	Harmonized as EN 60598-2-5
IEC 60634	NOTE	Harmonized as EN 60634
IEC 60664 (series)	NOTE	Harmonized as EN 60664 (series)
IEC 60664-1:2007	NOTE	Harmonized as EN 60664-1:2007 (not modified)
IEC 60664-3	NOTE	Harmonized as EN 60664-3
IEC 60682	NOTE	Harmonized as EN 60682
IEC 60695 (series)	NOTE	Harmonized as EN 60695 (series)
IEC 60695-2 (series)	NOTE	Harmonized as EN 60695-2-13:2010/A1 (series)
IEC 60695-10-2	NOTE	Harmonized as EN 60695-10-2
IEC 60838 (series)	NOTE	Harmonized as EN 60838 (series)
IEC 60901	NOTE	Harmonized as EN 60901
IEC 60921	NOTE	Harmonized as EN 60921
IEC 60923	NOTE	Harmonized as EN 60923
IEC 60929	NOTE	Harmonized as EN 60929
IEC 60950-1:2005	NOTE	Harmonized as EN 60950-1:2006
IEC 61184	NOTE	Harmonized as EN 61184
IEC 61195	NOTE	Harmonized as EN 61195
IEC 61199:2011	NOTE	Harmonized as EN 61199:2011 (not modified)
IEC 61199:2011/A1:2012	NOTE	Harmonized as EN 61199:2011/A1:2013 (not modified)
IEC 61199:2011/A2:2014	NOTE	Harmonized as EN 61199:2011/A2:2015 (not modified)
IEC 61210	NOTE	Harmonized as EN 61210
IEC 61558-2-5	NOTE	Harmonized as EN 61558-2-5
IEC 61995 (series)	NOTE	Harmonized as EN 61995-2:2009/A1 (series)
IEC 62031	NOTE	Harmonized as EN IEC 62031
IEC 62035	NOTE	Harmonized as EN 62035
IEC 62368 (series)	NOTE	Harmonized as EN IEC 62368 (series)
IEC 62471:2006	NOTE	Harmonized as EN 62471:2008
IEC 62504:2014	NOTE	Harmonized as EN 62504:2014 (not modified)

## Annex ZA (normative)

### Normative references to international publications with their corresponding European publications

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

NOTE 1 Where an International Publication has been modified by common modifications, indicated by (mod), the relevant EN/HD applies.

NOTE 2 Up-to-date information on the latest versions of the European Standards listed in this annex is available here: [www.cenelec.eu](http://www.cenelec.eu).

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60061	Series	Lamp caps and holders together with gauges for the control of interchangeability and safety	EN 60061	Series
IEC 60061-2 (mod)		Lamp caps and holders together with gauges for the control of interchangeability and safety - Part 2: Lampholders	EN 60061-2 + A1 to A54	1993
IEC 60061-3		Lamp caps and holders together with gauges for the control of interchangeability and safety - Part 3: Gauges	EN 60061-3 + A1 to A56	1993
IEC 60065 (mod)	2014	Audio, video and similar electronic apparatus - Safety requirements	EN 60065 + A11	2014 2017
IEC 60068-2-6	2007	Environmental testing – Part 2-6: Tests – Test Fc: Vibration (sinusoidal)	EN 60068-2-6	2008
IEC 60068-2-14	2009	Environmental testing – Part 2-14: Tests – Test N: Change of temperature	EN 60068-2-14	2009
IEC 60068-2-31	2008	Environmental testing – Part 2-31: Tests – Test Ec: Rough handling shocks, primarily for equipment-type specimens	EN 60068-2-31	2008
IEC 60068-2-75		Environmental testing - Part 2-75: Tests - Test Eh: Hammer tests	EN 60068-2-75	2014
IEC/TR 60083	–	Plugs and socket-outlets for domestic and similar general use standardized in member countries of IEC	–	–
IEC 60085		Electrical insulation - Thermal evaluation and designation	EN 60085	2008
IEC 60112	2003	Method for the determination of the proof and the comparative tracking indices of solid insulating materials	EN 60112	2003
IEC 60155		Glow-starters for fluorescent lamps	EN 60155 + A1 + A2	1995 1995 2007

**EN IEC 60598-1:2021 (E)**

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>	
IEC 60227	Series	Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V	EN 50525 <sup>1</sup>	Series	
IEC 60238	2016	Edison screw lampholders	EN IEC 60238	2018	
IEC 60245	series	Rubber insulated cables - Rated voltages up to and including 450/750 V	EN 50525 <sup>2</sup>	series	
IEC 60320	Series	Appliance couplers for household and similar general purposes	EN 60320	Series	
IEC 60360		Standard method of measurement of lamp cap temperature rise	EN 60360	1998	
IEC 60384-14		Fixed capacitors for use in electronic equipment - Part 14: Sectional specification - Fixed capacitors for electromagnetic interference suppression and connection to the supply mains	EN 60384-14 + A1	2013 2016	
IEC 60417	data-base	Graphical symbols for use on equipment	-	-	
IEC 60432-1 (mod)	1999	Incandescent lamps - Safety specifications - Part 1: Tungsten filament lamps for domestic and similar general lighting purposes	EN 60432-1	2000	
A1	2005			A1	2005
A2	2011			A2	2012
IEC 60432-2 (mod)	1999	Incandescent lamps - Safety specifications - Part 2: Tungsten halogen lamps for domestic and similar general lighting purposes	EN 60432-2	2000	
A1 (mod)	2005			A1	2005
A2	2012			A2	2012
IEC 60529	-	Degrees of protection provided by enclosures (IP Code)	EN 60529 + corr. May + A1 + A2	1991	
				1993	
				2000	
				2013	
IEC 60570 (mod)	2003	Electrical supply track systems for luminaires	EN 60570	2003	
+ A1	2017			+ A1	2018
+ A2	2019			+ A2	2020
IEC 60598-2	series	Luminaires - Part 2: Particular requirements	EN 60598-2	series	
IEC 60598-2-4 (mod)	2017	Luminaires - Part 2: Particular requirements - Section 4: Portable general purpose luminaires	EN 60598-2-4	2018	
IEC 60603	series	Connectors for frequencies below 3 MHz for use with printed boards	EN 60603	series	
IEC 60662 (mod)	-	High pressure sodium vapour lamps	EN 60662 + A11	2012	
				2019	
IEC 60664-4	2005	Insulation coordination for equipment within low-voltage systems - Part 4: Consideration of high-frequency voltage stress	EN 60664-4	2006	
-	-		+ corrigendum Oct. 2006		

<sup>1</sup> EN 50525 Series, which is related to, but not directly equivalent with IEC 60227 Series, applies instead.

<sup>2</sup> EN 50525 Series, which is related to, but not directly equivalent with IEC 60245 Series, applies instead.

**EN IEC 60598-1:2021 (E)**

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
IEC 60684	series	Flexible insulating sleeving	EN 60684	series
IEC 60695-2-11	-	Fire hazard testing - Part 2-11: Glowing/hot-wire based test methods - Glow-wire flammability test method for end-products (GWEPT)	EN 60695-2-11	2014
IEC 60695-11-5	-	Fire hazard testing - Part 11-5: Test flames - Needle-flame test method - Apparatus, confirmatory test arrangement and guidance	EN 60695-11-5	2017
IEC 60989	-	Separating transformers, autotransformers, - variable transformers and reactors.	-	-
IEC 60990	-	Methods of measurement of touch current and protective conductor current	EN 60990	2016
IEC 60998-2-1	-	Connecting devices for low-voltage circuits for household and similar purposes - Part 2-1: Particular requirements for connecting devices as separate entities with screw-type clamping units	EN 60998-2-1	2004
IEC 60998-2-2	-	Connecting devices for low-voltage circuits for household and similar purposes - Part 2-2: Particular requirements for connecting devices as separate entities with screwless-type clamping units	EN 60998-2-2	2004
IEC 61032	1997	Protection of persons and equipment by enclosures - Probes for verification	EN 61032	1998
IEC 61058-1	2000	Switches for appliances -- Part 1: General requirements	EN 61058-1	2002 <sup>3</sup>
IEC 61167	-	Metal halide lamps	EN 61167 + A1	2018 2018
IEC 61249	series	Materials for printed boards and other interconnecting structures	EN 61249	series
IEC 61347	series	Lamp controlgear	EN 61347	series
IEC 61347-1	2015	Lamp controlgear - Part 1: General and safety requirements	EN 61347-1	2015
+ A1	2017		+ A1	2021
IEC 61347-2-9	-	Lamp controlgear - Part 2-9: Particular requirements for electromagnetic controlgear for discharge lamps (excluding fluorescent lamps)	EN 61347-2-9	2013
IEC 61535 (mod)	2009	Installation couplers intended for permanent connection in fixed installations	EN 61535	2009
IEC 61558	series	Safety of power transformers, power supplies, reactors and similar products	EN 61558	series
IEC 61558-1	2005	Safety of power transformers, power supplies, reactors and similar products -- Part 1: General requirements and tests	EN 61558-1	2005

---

<sup>3</sup> EN 61058-1 includes A1:2001 to IEC 61058-1 (mod).



**EN IEC 60598-1:2021 (E)**

<u>Publication</u>	<u>Year</u>	<u>Title</u>	<u>EN/HD</u>	<u>Year</u>
-	-		+ corrigendum Aug.2006	
IEC 61558-2-6	-	Safety of transformers, reactors, power supply units and similar products for supply voltages up to 1 100 V - Part 2-6: Particular requirements and tests for safety isolating transformers and power supply units incorporating safety isolating transformers	EN 61558-2-6	2009
IEC 61643-11	-	Low-voltage surge protective devices - Part 11: Surge protective devices connected to low-voltage power systems - Requirements and test methods	EN 61643-11 + A11	2012 2018
IEC 61984	2008	Connectors - Safety requirements and tests	EN 61984	2009
IEC 62368-3	2017	Audio/video, information and communication technology equipment - Part 3: Safety aspects for DC power transfer through communication cables and ports	EN IEC 62368-3	2020
IEC 62493	2015	Assessment of lighting equipment related to human exposure to electromagnetic fields	EN 62493	2015
IEC 62680	series	Universal Serial Bus interfaces for data and power	EN 62680	series
IEC/TR 62778	-	Application of IEC 62471 for the assessment of blue light hazard to light sources and luminaires	IEC/TR 62778	2014
IEC 80416-1	-	Basic principles for graphical symbols for use on equipment - Part 1: Creation of graphical symbols for registration	EN 80416-1	2009

## Annex ZZ (informative)

### Relationship between this European standard and the safety objectives of Directive 2014/35/EU [2014 OJ L96] aimed to be covered

This European Standard has been prepared under a Commission's standardization request relating to harmonized standards in the field of the Low Voltage Directive, M/511, to provide one voluntary means of conforming to safety objectives of Directive 2014/35/EU of the European Parliament and of the Council of 26 February 2014 on the harmonization of the laws of the Member States relating to the making available on the market of electrical equipment designed for use within certain voltage limits [2014 OJ L96].

Once this standard is cited in the Official Journal of the European Union under that Directive, compliance with the normative clauses of this standard given in Table ZZ.1 confers, within the limits of the scope of this standard, a presumption of conformity with the corresponding safety objectives of that Directive, and associated EFTA regulations.

**Table ZZ.1 — Correspondence between this European standard and Annex I of Directive 2014/35/EU [2014 OJ L96]**

Safety objectives of Directive 2014/35/EU	Clause(s) / sub-clause(s) of this EN	Remarks / Notes
<b>1. General conditions</b>		
a) the essential characteristics, the recognition and observance of which will ensure that electrical equipment will be used safely and in applications for which it was made, shall be marked on the electrical equipment, or, if this is not possible, on an accompanying document;	Section 3	To be used in conjunction with relevant part 2
b) the electrical equipment, together with its component parts, shall be made in such a way as to ensure that it can be safely and properly assembled and connected;	Section 4	To be used in conjunction with relevant part 2
c) the electrical equipment shall be so designed and manufactured as to ensure that protection against the hazards set out in points 2 and 3 is assured, providing that the equipment is used in applications for which it was made and is adequately maintained.	See item 2 and 3 of this table	

<b>Safety objectives of Directive 2014/35/EU</b>	<b>Clause(s) / sub-clause(s) of this EN</b>	<b>Remarks / Notes</b>
<p><b>2. Protection against hazards arising from the electrical equipment</b></p> <p>Measures of a technical nature shall be laid down in accordance with point 1, in order to ensure that:</p>		
<p>a) persons and domestic animals are adequately protected against the danger of physical injury or other harm which might be caused by direct or indirect contact;</p>	<p>Section 4 Section 7 Section 14 and 15 Section 5 Section 8</p>	<p>All to be used in conjunction with relevant part 2</p>
<p>b) temperatures, arcs or radiation which would cause a danger, are not produced;</p>	<p>Section 4 Section 11 Section 12 Section 10</p>	<p>All to be used in conjunction with relevant part 2</p>
<p>c) persons, domestic animals and property are adequately protected against non-electrical dangers caused by the electrical equipment which are revealed by experience;</p>	<p>Section 4 Section 10 Section 11</p>	<p>All to be used in conjunction with relevant part 2</p>
<p>d) the insulation is suitable for foreseeable conditions.</p>	<p>Section 9 Section 10</p>	<p>All to be used in conjunction with relevant part 2</p>
<p><b>3. Protection against hazards which may be caused by external influences on the electrical equipment</b></p> <p>Technical measures shall be laid down in accordance with point 1, in order to ensure that the electrical equipment:</p>		
<p>a) meets the expected mechanical requirements in such a way that persons, domestic animals and property are not endangered;</p>	<p>Section 3 Section 4</p>	<p>All to be used in conjunction with relevant part 2</p>
<p>b) is resistant to non-mechanical influences in expected environmental conditions, in such a way that persons, domestic animals and property are not endangered;</p>	<p>Section 9 Section 13</p>	<p>All to be used in conjunction with relevant part 2</p>
<p>c) does not endanger persons, domestic animals and property in foreseeable conditions of overload.</p>	<p>Section 4 Section 12</p>	<p>All to be used in conjunction with relevant part 2</p>

**EN IEC 60598-1:2021 (E)**

**WARNING 1** — Presumption of conformity stays valid only as long as a reference to this European standard is maintained in the list published in the Official Journal of the European Union. Users of this standard should consult frequently the latest list published in the Official Journal of the European Union.

**WARNING 2** — Other Union legislation may be applicable to the product(s) falling within the scope of this standard.



**IEC 60598-1**

Edition 9.0 2020-08

# **INTERNATIONAL STANDARD**

---

**Luminaires –  
Part 1: General requirements and tests**



**THIS PUBLICATION IS COPYRIGHT PROTECTED****Copyright © 2020 IEC, Geneva, Switzerland**

All rights reserved. Unless otherwise specified, no part of this publication may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm, without permission in writing from either IEC or IEC's member National Committee in the country of the requester. If you have any questions about IEC copyright or have an enquiry about obtaining additional rights to this publication, please contact the address below or your local IEC member National Committee for further information.

IEC Central Office  
3, rue de Varembe  
CH-1211 Geneva 20  
Switzerland

Tel.: +41 22 919 02 11  
[info@iec.ch](mailto:info@iec.ch)  
[www.iec.ch](http://www.iec.ch)

**About the IEC**

The International Electrotechnical Commission (IEC) is the leading global organization that prepares and publishes International Standards for all electrical, electronic and related technologies.

**About IEC publications**

The technical content of IEC publications is kept under constant review by the IEC. Please make sure that you have the latest edition, a corrigendum or an amendment might have been published.

**IEC publications search - [webstore.iec.ch/advsearchform](http://webstore.iec.ch/advsearchform)**

The advanced search enables to find IEC publications by a variety of criteria (reference number, text, technical committee,...). It also gives information on projects, replaced and withdrawn publications.

**IEC Just Published - [webstore.iec.ch/justpublished](http://webstore.iec.ch/justpublished)**

Stay up to date on all new IEC publications. Just Published details all new publications released. Available online and once a month by email.

**IEC Customer Service Centre - [webstore.iec.ch/csc](http://webstore.iec.ch/csc)**

If you wish to give us your feedback on this publication or need further assistance, please contact the Customer Service Centre: [sales@iec.ch](mailto:sales@iec.ch).

**Electropedia - [www.electropedia.org](http://www.electropedia.org)**

The world's leading online dictionary on electrotechnology, containing more than 22 000 terminological entries in English and French, with equivalent terms in 16 additional languages. Also known as the International Electrotechnical Vocabulary (IEV) online.

**IEC Glossary - [std.iec.ch/glossary](http://std.iec.ch/glossary)**

67 000 electrotechnical terminology entries in English and French extracted from the Terms and Definitions clause of IEC publications issued since 2002. Some entries have been collected from earlier publications of IEC TC 37, 77, 86 and CISPR.



IEC 60598-1

Edition 9.0 2020-08

# INTERNATIONAL STANDARD

---

## Luminaires – Part 1: General requirements and tests

INTERNATIONAL  
ELECTROTECHNICAL  
COMMISSION

---

ICS 29.140.40

ISBN 978-2-8322-8682-1

**Warning! Make sure that you obtained this publication from an authorized distributor.**

## CONTENTS

FOREWORD .....	9
SECTION 0: GENERAL INTRODUCTION .....	12
0.1 Scope .....	12
0.2 Normative references .....	13
0.3 General requirements .....	16
0.4 General test requirements and verification .....	16
0.5 Components of luminaires .....	17
0.6 List of parts of IEC 60598-2 .....	18
0.7 Information for luminaire design in light sources standards .....	19
SECTION 1: TERMS AND DEFINITIONS .....	20
1.1 General .....	20
1.2 Terms and definitions .....	20
SECTION 2: CLASSIFICATION OF LUMINAIRES .....	36
2.1 General .....	36
2.2 Classification according to type of protection against electric shock .....	36
2.3 Classification according to degree of protection against ingress of dust, solid objects and moisture .....	36
2.4 Classification according to material of supporting surface for which the luminaire is designed .....	36
2.5 Classification according to the circumstances of use .....	37
SECTION 3: MARKING .....	38
3.1 General .....	38
3.2 Marking on luminaires .....	38
3.3 Additional information .....	44
3.4 Test of marking .....	47
SECTION 4: CONSTRUCTION .....	48
4.1 General .....	48
4.2 Replaceable components .....	48
4.3 Wireways .....	48
4.4 Lampholders .....	48
4.5 Starterholders .....	50
4.6 Terminal blocks .....	50
4.7 Terminals and supply connections .....	51
4.8 Switches .....	53
4.9 Insulating linings and sleeves .....	53
4.10 Double and reinforced insulation .....	54
4.11 Electrical connections and current-carrying parts .....	56
4.12 Screws and connections (mechanical) and glands .....	57
4.13 Mechanical strength .....	60
4.14 Suspensions, fixings and means of adjustment .....	63
4.15 Flammable materials .....	67
4.16 Luminaires for mounting on normally flammable surfaces .....	68
4.17 Drain holes .....	70
4.18 Resistance to corrosion .....	70
4.19 Ignitors .....	70
4.20 Rough service luminaires – Vibration requirements .....	71



4.21	Protective shield .....	71
4.22	Attachments to lamps.....	72
4.23	Semi-luminaires .....	72
4.24	Photobiological hazards .....	72
4.25	Mechanical hazard .....	73
4.26	Short-circuit protection.....	73
4.27	Terminal blocks with integrated screwless protective earthing contacts.....	74
4.28	Fixing of thermal sensing controls.....	74
4.29	Luminaire with non-replaceable light source.....	75
4.30	Luminaires with non-user replaceable light sources .....	75
4.31	Insulation between circuits.....	75
4.32	Overvoltage protective devices .....	77
4.33	Luminaire powered via information technology communication cabling.....	78
4.34	Electromagnetic fields (EMF) .....	78
4.35	Protection against moving fan blades.....	78
4.36	Track-mounted luminaires.....	78
SECTION 5: EXTERNAL AND INTERNAL WIRING .....		79
5.1	General.....	79
5.2	Supply connection and other external wiring .....	79
5.3	Internal wiring .....	87
5.4	Test to determine suitability of conductors having a reduced cross-sectional area .....	89
SECTION 6: Void.....		91
SECTION 7: PROVISION FOR EARTHING .....		92
7.1	General.....	92
7.2	Provision for earthing.....	92
SECTION 8: PROTECTION AGAINST ELECTRIC SHOCK .....		95
8.1	General.....	95
8.2	Protection against electric shock.....	95
SECTION 9: RESISTANCE TO DUST, SOLID OBJECTS AND MOISTURE .....		99
9.1	General.....	99
9.2	Tests for ingress of dust, solid objects and moisture .....	99
9.3	Humidity test.....	103
SECTION 10: INSULATION RESISTANCE AND ELECTRIC STRENGTH, TOUCH CURRENT AND PROTECTIVE CONDUCTOR CURRENT.....		105
10.1	General.....	105
10.2	Insulation resistance and electric strength .....	105
10.3	Touch current, protective conductor current and electric burn .....	109
SECTION 11: CREEPAGE DISTANCES AND CLEARANCES .....		111
11.1	General.....	111
11.2	Creepage distances and clearances.....	111
SECTION 12: ENDURANCE TEST AND THERMAL TEST.....		115
12.1	General.....	115
12.2	Selection of lamps and ballasts .....	115
12.3	Endurance test.....	115
12.4	Thermal test (normal operation) .....	117
12.5	Thermal test (abnormal operation) .....	122
12.6	Thermal test (failed windings in lamp controlgear) .....	127

12.7	Thermal test in regard to fault conditions in lamp controlgear or electronic devices incorporated in thermoplastic luminaires .....	129
SECTION 13: RESISTANCE TO HEAT, FIRE AND TRACKING.....		132
13.1	General.....	132
13.2	Resistance to heat .....	132
13.3	Resistance to flame and ignition .....	132
13.4	Resistance to tracking.....	133
SECTION 14: SCREW TERMINALS.....		134
14.1	General.....	134
14.2	Terms and definitions.....	134
14.3	General requirements and basic principles.....	135
14.4	Mechanical tests .....	137
SECTION 15: SCREWLESS TERMINALS AND ELECTRICAL CONNECTIONS.....		141
15.1	General.....	141
15.2	Terms and definitions.....	141
15.3	General requirements .....	141
15.4	General instructions on tests.....	143
15.5	Terminal and connections for internal wiring .....	143
15.6	Terminals and connections for external wiring.....	146
Annex A (normative) Test to establish whether a conductive part can cause an electric shock.....		173
Annex B (normative) Test lamps .....		174
B.1	General.....	174
B.2	Filament lamps within the scope of IEC 60432-1 and IEC 60432-2.....	174
B.3	Halogen lamps within the scope of IEC 60432-3 .....	176
B.4	Tubular fluorescent and other discharge lamps .....	176
B.5	LED modules within the scope of IEC 62031 .....	176
Annex C (normative) Abnormal circuit conditions .....		177
Annex D (normative) Thermal testing .....		180
D.1	Draught-proof enclosure .....	180
D.2	Mounting surface and test recess.....	180
D.3	Alternative test procedure for adjustment of measured temperatures for luminaire $t_a$ rating(s).....	183
Annex E (normative) Determination of winding temperature rises by the increase-in-resistance method .....		185
Annex F (normative) Test for resistance to stress corrosion of copper and copper alloys.....		186
F.1	Test cabinet.....	186
F.2	Test solution .....	186
F.3	Test piece .....	186
F.4	Test procedure.....	186
Annex G (normative) Measurement of touch current and protective conductor current .....		188
Annex H (xxx) (Void).....		192
Annex I (xxx) (Void) .....		193
Annex J (informative) Explanation of IP numbers for degrees of protection .....		194
Annex K (informative) Temperature measurement.....		196
K.1	Temperature measurements of the luminaire .....	196
K.2	Temperature measurement of the insulation parts of lampholders .....	197

Annex L (informative) Guidelines for good practice in luminaire design .....	199
L.1 General.....	199
L.2 Plastics in luminaires .....	199
L.3 Rust resistance .....	200
L.4 Corrosion resistance .....	200
L.5 Chemically corrosive atmospheres .....	201
L.6 Reflector design.....	201
L.7 Components in different kinds of luminaires .....	202
L.8 Recommendations for electromagnetic ballast protection for end of life phenomenon of HID lamps .....	202
L.9 Resistance against the effects of vibration .....	203
L.10 Flammability of components.....	203
Annex M (normative) Determination of creepage distances and clearances .....	204
Annex N (informative) Explanation of marking for luminaires that are not suitable for mounting on normally flammable surfaces and covering with insulation materials .....	205
N.0 General.....	205
N.1 Protection against flame .....	205
N.2 Protection against heat .....	205
N.3 Thermal protectors.....	206
N.4 Deletion of the F mark requirements .....	207
Annex O (xxx) (Void) .....	208
Annex P (normative) Absorption requirements for the protective shield to be fitted to luminaires designed for metal halide lamps which emit a high level of UV radiation .....	209
P.1 General.....	209
P.2 Procedure A.....	209
P.3 Procedure B.....	210
Annex Q (informative) Conformity testing during manufacture .....	211
Q.1 General.....	211
Q.2 Testing .....	211
Annex R (normative) Schedule of amended clauses and subclauses containing more serious/critical requirements which call for products to be retested .....	213
Annex S (normative) Requirements for the identification of a family or range of luminaires for type testing.....	214
S.1 General.....	214
S.2 Range or family of luminaires.....	214
Annex T (xxx) (Void) .....	215
Annex U (informative) Additional requirements for luminaires where a higher degree of availability (impulse withstand category III) may be requested .....	216
U.1 General.....	216
U.2 Requirements for impulse withstand category III .....	216
Annex V (normative) Additional test requirements for terminal blocks with integrated screwless protective earthing contact for direct connection to the luminaire housing or to parts of the body .....	218
V.1 Additional requirements to 7.2.1.....	218
V.2 Additional requirements to 7.2.3.....	218
Annex W (normative) Alternative thermal test for thermoplastic luminaires.....	220
W.1 Thermal test in regard to fault conditions in lamp controlgear or electronic devices without temperature sensing controls in thermoplastic luminaires for fluorescent lamps ≤ 70 W.....	220

Annex X (normative) Requirements for insulation between active parts of circuits and accessible conductive parts .....	222
Annex Y (informative) Information regarding power sourcing equipment powering class III luminaires via information technology communication cabling .....	224
Y.0 General.....	224
Y.1 Insulation of the mains supply .....	224
Y.2 Electrical limits of a PSE.....	224
Bibliography.....	226
Figure 34 – Circuit for checking electrical contact between socket outlet and plug .....	85
Figure 33 – Test to determine suitability of conductors having a reduced cross-sectional area .....	90
Figure 1 – Symbols .....	149
Figure 2 – Terminal block arrangement for installation test for luminaires with connecting leads (tails) .....	152
Figure 3 – Void .....	152
Figure 4 – Illustration of the requirements of 4.15 .....	152
Figure 5 – Void .....	152
Figure 6 – Apparatus for proving protection against dust.....	153
Figure 7 – Apparatus for testing protection against rain and splashing.....	154
Figure 8 – Nozzle for spray test .....	155
Figure 9 – Relation between winding temperature and mounting surface temperature.....	156
Figure 10 – Ball-pressure apparatus .....	157
Figure 11 – Arrangement and dimensions of the electrodes for the tracking test .....	157
Figure 12 – Pillar terminals .....	158
Figure 13 – Screw terminals and stud terminals .....	159
Figure 14 – Saddle terminals .....	161
Figure 15 – Lug terminals .....	162
Figure 16 – Mantle terminals.....	163
Figure 17 – Construction of electrical connections .....	164
Figure 18 – Examples of spring-type screwless terminals .....	164
Figure 19 – Further examples of screwless terminals.....	165
Figure 20 – Illustration of the terms "lopping-in" and "through wiring".....	166
Figure 21 – Apparatus for ball impact tests .....	167
Figure 22 – Examples of self-tapping, thread-cutting and thread-forming screws (from ISO 1891) .....	167
Figure 23 – Void .....	167
Figure 24 – Illustration of creepage and clearance measurements at a supply terminal.....	168
Figure 25 – Void .....	168
Figure 26 – Test circuit for safety during insertion.....	168
Figure 27 – Ignition temperatures of wood as a function of time .....	169
Figure 28 – Example of permitted degree of soldering .....	170
Figure 29 – Test chain .....	170
Figure 30 – Example of a thread forming screw used in a groove of a metallic material .....	171
Figure 31 – Electro-mechanical contact system with plug/socket connection.....	172

Figure 32 – Test circuit for luminaires incorporating fluorescent lamp $\leq 70$ W .....	172
Figure C.1 – Circuit for testing rectifying effect (some capacitive starterless ballasts only) .....	178
Figure C.2 – Circuit for testing rectifying effect (ballasts for single pin lamps) .....	178
Figure C.3 – Circuit for testing rectifying effect of some high pressure sodium and some metal halide lamps .....	179
Figure D.1 – Example of test recess where a luminaire comprises separate parts, in accordance with Clause D.2 a) .....	181
Figure D.2 – Example of test recess where a luminaire comprises separate parts, in accordance with Clause D.2 b) .....	182
Figure D.3 – Correct test box size (insulating ceilings) for settable and adjustable luminaires .....	183
Figure G.1 – Test configuration: single-phase equipment on star TN or TT system .....	190
Figure G.2 – Measuring network, touch current weighted for perception or reaction .....	190
Figure G.3 – Measuring network, touch current weighted for let-go (for portable class I luminaires) .....	191
Figure G.4 – Measuring network, weighted for high frequency .....	191
Figure K.1 – Placing of thermocouples on a typical lampholder .....	198
Figure V.1 – Arrangement for voltage drop test .....	219
Figure X.1 – Declaration of $LV_{\text{supply}}$ and $U_{\text{out}}$ and the insulation barriers between the light source and accessible parts .....	222
Table 3.1 – Marking .....	39
Table 3.2 – Identification of extra-low-voltage DC leads and terminations .....	41
Table 4.6 – Overview of required Y capacitors .....	55
Table 4.1 – Torque tests on screws .....	58
Table 4.2 – Torque tests on cable glands .....	60
Table 4.3 – Impact energy and spring compression .....	61
Table 4.4 – Test on semi-luminaires .....	65
Table 4.5 – Test on adjusting devices .....	66
Table 5.1 – Supply cord .....	80
Table 5.3 – Wiring dimension .....	81
Table 5.2 – Tests for cord anchorage .....	84
Table 9.1 – Solid-object-proof luminaire test .....	101
Table 10.1 – Minimum insulation resistance .....	106
Table 10.2 – Electric strength .....	108
Table 10.3 – Limits of touch current or protective conductor current and electric burn .....	110
Table 11.1.A – Minimum creepage distances for AC sinusoidal voltages up to 30 kHz (to be used in conjunction with Annex M) .....	113
Table 11.1.B – Minimum clearance for working voltages (to be used in conjunction with Annex M) .....	114
Table 11.2 – Minimum distances for ignition pulse voltages or equivalent peak voltage $U_p$ .....	114
Table 12.1 – Maximum temperatures under the test conditions of 12.4.2, for principal parts .....	120
Table 12.2 – Maximum temperatures under the test conditions of 12.4.2, for common materials used in luminaires .....	122

Table 12.3 – Maximum temperatures under the test conditions of 12.5.1 .....	125
Table 12.4 – Maximum temperature of windings under abnormal operating conditions and at 110 % of rated voltage for lamp controlgear .....	126
Table 12.5 – Maximum temperature of windings under abnormal operating conditions and at 110 % of rated voltage for lamp controlgear marked "D6" .....	126
Table 12.6 – Temperature overshoot time limitation .....	128
Table 14.1 – Nominal cross-sectional areas of conductors according to terminal sizes .....	136
Table 14.2 – Nominal cross-sectional areas of conductors according to maximum current .....	136
Table 14.3 – Composition of conductors .....	137
Table 14.4 – Torque to be applied to screws and nuts .....	139
Table 14.5 – Pull to be applied to conductor .....	140
Table 15.1 – Conductor rating .....	146
Table 15.2 – Conductor pull force .....	147
Table F.1 – pH value of the test solution .....	186
Table G.1 – Position of switch e, n and p for the measurements of the different classes of luminaires .....	189
Table J.1 – Degrees of protection indicated by the first characteristic numeral .....	194
Table J.2 – Degrees of protection indicated by the second characteristic numeral .....	195
Table L.1 – Damaging influences .....	199
Table M.1 – Determination of creepage distances and clearances (see Table 11.1) .....	204
Table N.1 – Guidance on when to use the symbol and its explanation on the luminaire or in the manufacturer's instructions provided with the luminaire .....	205
Table N.2 – Thermal protection operation .....	207
Table Q.1 – Minimum values for electrical tests .....	212
Table U.1 – Minimum clearance distances for AC sinusoidal working voltages impulse withstand category III .....	216
Table U.2 – Overview of required Y capacitors .....	217
Table X.1 – Insulation requirements between active parts and accessible conductive parts .....	223
Table Y.1 – Limits for the electrical parameters of a PSE .....	224
Table Y.2 – Electrical parameters for communication cable/connectors .....	225

# INTERNATIONAL ELECTROTECHNICAL COMMISSION

---

## LUMINAIRES –

### Part 1: General requirements and tests

#### FOREWORD

- 1) The International Electrotechnical Commission (IEC) is a worldwide organization for standardization comprising all national electrotechnical committees (IEC National Committees). The object of IEC is to promote international co-operation on all questions concerning standardization in the electrical and electronic fields. To this end and in addition to other activities, IEC publishes International Standards, Technical Specifications, Technical Reports, Publicly Available Specifications (PAS) and Guides (hereafter referred to as "IEC Publication(s)"). Their preparation is entrusted to technical committees; any IEC National Committee interested in the subject dealt with may participate in this preparatory work. International, governmental and non-governmental organizations liaising with the IEC also participate in this preparation. IEC collaborates closely with the International Organization for Standardization (ISO) in accordance with conditions determined by agreement between the two organizations.
- 2) The formal decisions or agreements of IEC on technical matters express, as nearly as possible, an international consensus of opinion on the relevant subjects since each technical committee has representation from all interested IEC National Committees.
- 3) IEC Publications have the form of recommendations for international use and are accepted by IEC National Committees in that sense. While all reasonable efforts are made to ensure that the technical content of IEC Publications is accurate, IEC cannot be held responsible for the way in which they are used or for any misinterpretation by any end user.
- 4) In order to promote international uniformity, IEC National Committees undertake to apply IEC Publications transparently to the maximum extent possible in their national and regional publications. Any divergence between any IEC Publication and the corresponding national or regional publication shall be clearly indicated in the latter.
- 5) IEC itself does not provide any attestation of conformity. Independent certification bodies provide conformity assessment services and, in some areas, access to IEC marks of conformity. IEC is not responsible for any services carried out by independent certification bodies.
- 6) All users should ensure that they have the latest edition of this publication.
- 7) No liability shall attach to IEC or its directors, employees, servants or agents including individual experts and members of its technical committees and IEC National Committees for any personal injury, property damage or other damage of any nature whatsoever, whether direct or indirect, or for costs (including legal fees) and expenses arising out of the publication, use of, or reliance upon, this IEC Publication or any other IEC Publications.
- 8) Attention is drawn to the Normative references cited in this publication. Use of the referenced publications is indispensable for the correct application of this publication.
- 9) Attention is drawn to the possibility that some of the elements of this IEC Publication may be the subject of patent rights. IEC shall not be held responsible for identifying any or all such patent rights.

International Standard IEC 60598-1 has been prepared by subcommittee 34D: Luminaires, of IEC technical committee 34: Lamps and related equipment.

This ninth edition cancels and replaces the eighth edition published in 2014 and Amendment 1:2017. This edition constitutes a technical revision.

This edition includes the following significant technical changes with respect to the previous edition:

- a) Revision of Clause 4.30, Fixing cover live parts of non-user replaceable light source;
- b) Subclause 4.24.2, Blue Light Hazard: removal of Risk Group 0;
- c) Subclause 5.2.16: additional requirements for AC mains appliance inlets related to IEC 61984;
- d) Addition of Subclause 3.3.25, UV protection of cable;
- e) Addition of Clause 4.34, Inclusion of EMF safety requirements (IEC 62493);

- f) Revision of the requirements for functional earth and protective earth;
- g) Addition of Clause 4.35, Protection against fast rotating parts;
- h) Revision of Clause 3.2, Rated voltage marking;
- i) Revision of Subclause 5.2.10, Cord anchorage;
- j) Revision of Annex G for touch current and protective conductor current test set-up;
- k) Addition of requirements for constant light output function and programmable current output;
- l) Revision of Subclause 8.2.3 c), touch voltage limits for interrupted DC voltage;
- m) Introduction of PELV;
- n) Introduction of Ethernet power supply connection for luminaires (PoE);
- o) Section 9, Introduction of IPX9;
- p) Addition of Subclause 3.3.26 for wall mounted luminaires;
- q) Revision of Annex D introducing alternative thermal tests for luminaires with  $t_a$  marking higher than 25°C;
- r) Revision of Table 10.3 and Subclause 3.3.19 for protective conductor current limits;
- s) Track-mounted luminaires: cross reference to Annex A of IEC 60570:2003/AMD2:2019;
- t) Revision of Subclause 10.2.2, alternative DC electric strength test;
- u) Revision of Annex D for recessed luminaires;
- v) Subclause 4.12.5: revision of Table 4.2 for torque test on metal glands;
- w) Revision of use of bridging capacitors in luminaires;
- x) Revision of electrical connection to class III plugs.

The major changes which may affect certification are given in Annex R.

Annex R shows where a new text has been included which contains more serious/critical requirements requiring products to be re-tested.

The text of this International Standard is based on the following documents:

FDIS	Report on voting
34D/1546/FDIS	34D/1560/RVD

Full information on the voting for the approval of this International Standard can be found in the report on voting indicated in the above table.

This document has been drafted in accordance with the ISO/IEC Directives, Part 2.

A list of all parts in the IEC 60598 series, published under the general title *Luminaires*, can be found on the IEC website.

NOTE In this document, the following print types are used:

- requirements: in roman type;
- *test specifications: in italic type;*
- notes: in small roman type.



The committee has decided that the contents of this document will remain unchanged until the stability date indicated on the IEC website under "<http://webstore.iec.ch>" in the data related to the specific document. At this date, the document will be

- reconfirmed,
- withdrawn,
- replaced by a revised edition, or
- amended.

**IMPORTANT – The 'colour inside' logo on the cover page of this publication indicates that it contains colours which are considered to be useful for the correct understanding of its contents. Users should therefore print this document using a colour printer.**

## LUMINAIRES –

### Part 1: General requirements and tests

#### SECTION 0: GENERAL INTRODUCTION

##### 0.1 Scope

This Part 1 of IEC 60598 specifies general requirements for luminaires, incorporating electric light sources for operation from supply voltages up to 1 000 V. The requirements and related tests of this document cover: classification, marking, mechanical construction, electrical construction and photobiological safety.

Each section of this Part 1 is read in conjunction with this Section 0 and with other relevant sections to which reference is made.

Each part of IEC 60598-2 details requirements for a particular type of luminaire or group of luminaires on supply voltages not exceeding 1 000 V. These parts are published separately for ease of revision and additional sections will be added as and when a need for them is recognized.

The presentation of photometric data for luminaires is under consideration by the International Commission on Illumination (CIE) and is not, therefore, included in this Part 1.

Requirements are included in this Part 1 for luminaires incorporating ignitors with nominal peak values of the voltage pulse not exceeding those of Table 11.2. The requirements apply to luminaires with ignitors built into ballasts and to luminaires with ignitors separate from ballasts. For luminaires with ignitors built into lamps, the requirements are under consideration.

Requirements for semi-luminaires are included in this Part 1.

In general, this Part 1 covers safety requirements for luminaires. The object of this Part 1 is to provide a set of requirements and tests which are considered to be generally applicable to most types of luminaires and which can be called up as required by the detail specifications of IEC 60598-2. This Part 1 is thus not regarded as a specification in itself for any type of luminaire, and its provisions apply only to particular types of luminaires to the extent determined by the appropriate part of IEC 60598-2.

The parts of IEC 60598-2, in making reference to any of the sections of Part 1, specify the extent to which that section is applicable and the order in which the tests are performed; they also include additional requirements as necessary.

The order in which the sections of Part 1 are numbered has no particular significance as the order in which their provisions apply is determined for each type of luminaire or group of luminaires by the appropriate part of IEC 60598-2. All parts of IEC 60598-2 are self-contained and therefore do not contain references to other parts of IEC 60598-2.

Where the requirements of any of the sections of Part 1 are referred to in the parts of IEC 60598-2 by the phrase "The requirements of section... of IEC 60598-1 apply", this phrase is interpreted as meaning that all the requirements of that section of Part 1 apply except those which are clearly inapplicable to the particular type of luminaire covered by that part of IEC 60598-2.

For explosion proof luminaires, as covered by IEC 60079, the requirements of IEC 60598 (selecting the appropriate parts 2) are applied in addition to the requirements of IEC 60079. In the event of any conflict between IEC 60598 and IEC 60079, the requirements of IEC 60079 take priority.

Improvements in safety to take into account the state of the art technology are incorporated in the standards with revisions and amendments on an ongoing basis. Regional standardization bodies can include statements in their derived standards to cover products which have complied with the previous document as shown by the manufacturer or standardization body. The statements may require that for such products, the previous standard may continue to apply to production until a defined date after which the new standard shall apply.

## 0.2 Normative references

The following documents are referred to in the text in such a way that some or all of their content constitutes requirements of this document. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

IEC 60061 (all parts), *Lamp caps and holders together with gauges for the control of interchangeability and safety* (available at <http://std.iec.ch/iec60061>)

IEC 60061-2, *Lamp caps and holders together with gauges for the control of interchangeability and safety – Part 2: Lampholders* (available at <http://std.iec.ch/iec60061>)

IEC 60061-3, *Lamp caps and holders together with gauges for the control of interchangeability and safety – Part 3: Gauges* (available at <http://std.iec.ch/iec60061>)

IEC 60065:2014, *Audio, video and similar electronic apparatus – Safety requirements*

IEC 60068-2-6:2007, *Environmental testing – Part 2-6: Tests – Test Fc: Vibration (sinusoidal)*

IEC 60068-2-14:2009, *Environmental testing – Part 2-14: Tests – Test N: Change of temperature*

IEC 60068-2-31:2008, *Environmental testing – Part 2-31: Tests – Test Ec: Rough handling shocks, primarily for equipment-type specimens*

IEC 60068-2-75, *Environmental testing – Part 2-75: Tests – Test Eh: Hammer tests*

IEC TR 60083, *Plugs and socket-outlets for domestic and similar general use standardized in member countries of IEC*

IEC 60085, *Electrical insulation – Thermal evaluation and designation*

IEC 60112:2003, *Method for the determination of the proof and the comparative tracking indices of solid insulating materials*

IEC 60155, *Glow-starters for fluorescent lamps*

IEC 60227 (all parts), *Polyvinyl chloride insulated cables of rated voltages up to and including 450/750 V*

IEC 60238:2016, *Edison screw lampholders*

IEC 60245 (all parts), *Rubber insulated cables – Rated voltages up to and including 450/750 V*

IEC 60320 (all parts), *Appliance couplers for household and similar general purposes*

IEC 60360, *Standard method of measurement of lamp cap temperature rise*

IEC 60384-14, *Fixed capacitors for use in electronic equipment – Part 14: Sectional specification – Fixed capacitors for electromagnetic interference suppression and connection to the supply mains*

IEC 60417, *Graphical symbols for use on equipment* (available at <http://www.graphical-symbols.info/equipment>)

IEC 60432-1:1999, *Incandescent lamps – Safety specifications – Part 1: Tungsten filament lamps for domestic and similar general lighting purposes*

IEC 60432-1:1999/AMD1:2005

IEC 60432-1:1999/AMD2:2011

IEC 60432-2:1999, *Incandescent lamps – Safety specifications –Part 2: Tungsten halogen lamps for domestic and similar general lighting purposes*

IEC 60432-2:1999/AMD1:2005

IEC 60432-2:1999/AMD2:2012

IEC 60529, *Degrees of protection provided by enclosures (IP Code)*

IEC 60570:2003, *Electrical supply track systems for luminaires*

IEC 60570:2003/AMD1:2017

IEC 60570:2003/AMD2:2019

IEC 60598-2 (all parts), *Luminaires – Part 2: Particular requirements*

IEC 60598-2-4:2017, *Luminaires – Part 2-4: Particular requirements – Portable general purpose luminaires*

IEC 60603 (all parts), *Connectors for frequencies below 3 MHz for use with printed boards*

IEC 60662, *High-pressure sodium vapour lamps – Performance specifications*

IEC 60664-4:2005, *Insulation coordination for equipment within low-voltage systems – Part 4: Consideration of high-frequency voltage stress*

IEC 60684 (all parts), *Flexible insulating sleeving*

IEC 60695-2-11, *Fire hazard testing – Part 2-11: Glowing/hot-wire based test methods – Glow-wire flammability test method for end-products (GWEPT)*

IEC 60695-11-5, *Fire hazard testing – Part 11-5: Test flames – Needle-flame test method – Apparatus, confirmatory test arrangement and guidance*

IEC 60989, *Separating transformers, autotransformers, variable transformers and reactors*

IEC 60990, *Methods of measurement of touch current and protective conductor current*

IEC 60998-2-1, *Connecting devices for low-voltage circuits for household and similar purposes – Part 2-1: Particular requirements for connecting devices as separate entities with screw-type clamping units*

IEC 60998-2-2, *Connecting devices for low-voltage circuits for household and similar purposes – Part 2-2: Particular requirements for connecting devices as separate entities with screwless-type clamping units*

IEC 61032:1997, *Protection of persons and equipment by enclosures – Probes for verification*

IEC 61058-1:20001, *Switches for appliances – Part 1: General requirements*

IEC 61167, *Metal halide lamps – Performance specification*

IEC 61249 (all parts), *Materials for printed boards and other interconnecting structures*

IEC 61347 (all parts), *Lamp controlgear*

IEC 61347-1:2015, *Lamp controlgear – Part 1: General and safety requirements*  
IEC 61347-1:2015/AMD1:2017

IEC 61347-2-9, *Lamp controlgear – Part 2-9: Particular requirements for electromagnetic controlgear for discharge lamps (excluding fluorescent lamps)*

IEC 61535:2009 <sup>2</sup>, *Installation couplers intended for permanent connection in fixed installations*

IEC 61558 (all parts), *Safety of power transformers, power supplies, reactors and similar products*

IEC 61558-1:2005 <sup>3</sup>, *Safety of power transformers, power supplies, reactors and similar products – Part 1: General requirements and tests*

IEC 61558-2-6, *Safety of transformers, reactors, power supply units and similar products for supply voltages up to 1 100 V – Part 2-6: Particular requirements and tests for safety isolating transformers and power supply units incorporating safety isolating transformers*

IEC 61643-11, *Low-voltage surge protective devices – Part 11: Surge protective devices connected to low-voltage power systems – Requirements and test methods*

IEC 61984:2008, *Connectors – Safety requirements and tests*

IEC 62368-3:2017, *Audio/video, information and communication technology equipment – Part 3: Safety aspects for DC power transfer through communication cables and ports*

IEC 62493:2015, *Assessment of lighting equipment related to human exposure to electromagnetic fields*

IEC 62680 (all parts), *Universal serial bus interfaces for data and power*

---

1 Withdrawn.

2 Withdrawn.

3 Withdrawn.

IEC TR 62778, *Application of IEC 62471 for the assessment of blue light hazard to light sources and luminaires*

IEC 80416-1, *Basic principles for graphical symbols for use on equipment – Part 1: Creation of graphical symbol for registration*

### **0.3 General requirements**

**0.3.1** Luminaires shall be so designed and constructed that in normal use they function safely and cause no danger to persons or surroundings. In general, compliance is checked by carrying out all the tests specified.

**0.3.2** A luminaire shall comply with a part of IEC 60598-2. If, however, an appropriate part of IEC 60598-2 does not exist for a particular luminaire or group of luminaires, the nearest applicable part of IEC 60598-2 may be used as a guide to the requirements and tests.

Where the design of a luminaire is such that two or more parts of IEC 60598-2 are applicable, the luminaire shall comply with both or all of the appropriate sections.

**0.3.3** Semi-luminaires should be regarded as luminaires for test purposes.

### **0.4 General test requirements and verification**

**0.4.1** Tests according to this document are type tests. For the definition of a "type test", see Section 1.

The requirements and tolerances permitted by this document are related to testing of a type test sample submitted for that purpose. Compliance of the type test sample does not ensure compliance of the whole production of a manufacturer. Compliance for production is the responsibility of the manufacturer and may include routine tests and quality assurance in addition to type testing.

**0.4.2** Except where otherwise specified in the sections of this document or relevant part of IEC 60598-2, luminaires shall be tested as delivered, and installed as for normal use, in an ambient temperature of between 10 °C and 30 °C, having regard to the manufacturer's installation instructions. The lamp (or lamps) is (are) not included except where essential for the test.

Luminaires cannot be regarded as meeting the requirements of this document unless all internal wiring is complete.

In general, the tests are made on a single sample luminaire or, where a range of similar luminaires is involved, on a single luminaire of each rated wattage in the range or on a representative selection from the range as agreed with the manufacturer (see Annex S). This selection shall include the luminaire, together with any attachments, which represents the most unfavourable combination from a testing point of view.

Each sample luminaire shall comply with all the relevant tests. In order to reduce the time of testing and to allow for any tests which may be destructive, the manufacturer may submit additional luminaires or parts of luminaires, provided that these are of the same materials and design as the original luminaire and that the results of the test are the same as if carried out on an identical luminaire. Where the test for compliance is shown as being "by inspection", this shall include any necessary handling.

For track-mounted luminaires the manufacturer shall provide, together with the luminaire, a sample of the appropriate track, connector and adaptors for the luminaire to be connected.

Combination luminaires are tested for safety requirements with that assemblage of parts which gives the most unfavourable result.

Certain parts of luminaires, such as joints, raising and lowering devices, may be tested separately provided that the design of these parts is such that their performance is not dependent upon the other parts of the luminaires.

Luminaires intended to be used with supply cords are tested with the flexible supply cord connected to the luminaire.

For luminaires intended to be used with a shade, but not normally supplied with a shade, the manufacturer shall provide a shade, typical of the type that might be used with the luminaire.

#### **0.4.3 Verification and tests**

Luminaires for testing to the requirements of this document may have earlier test reports updated in accordance with this document by submitting a new sample for test together with the previous test reports.

Full type testing need not generally be necessary and the product and the previous test results shall be reviewed only against any amended clauses marked "R" and scheduled in Annex R.

NOTE Clauses marked "R" and scheduled in Annex R will be included in future amendments/editions.

### **0.5 Components of luminaires**

**0.5.1** Components, other than integral components, shall comply with the requirements of the relevant IEC standards, if any.

Components which comply with the requirements of the relevant IEC standard and marked with individual ratings are checked to establish that they suit the conditions which may occur in use. Aspects of use not covered by the respective standard shall require them to satisfy the additional relevant requirements of this document.

Compliance is checked by inspection and the relevant tests.

Integral components shall comply as far as is reasonable with the IEC component standards, as part of the luminaire.

NOTE 1 This does not imply that components need to be separately tested before approval of the luminaire.

NOTE 2 Guidance on the selection of components in different kinds of luminaires can be found in Annex L.

Internal wiring of a luminaire shall comply with the requirements in 5.3.

NOTE 3 This does not exclude the use of standardized cables.

**0.5.2** Components complying with the requirements of their own standard and used in accordance with their intended use, shall only be tested to the requirements of this document where there are no requirements in the component standard (covering the requirement heading of this document).

A valid test report is considered adequate to show compliance.

Lampholders and starterholders shall additionally comply with the gauging and interchangeability requirements of the appropriate IEC component standard where applicable after building into the luminaire.

For terminal blocks with an integrated screwless protective earthing contact for direct connection to the luminaire or to parts of the body, special requirements apply according to Annex V.

**0.5.3** Components for which no appropriate IEC standard exists shall satisfy the relevant requirements of this luminaire standard as part of the luminaire. Lampholders and starterholders shall additionally comply with the gauging and interchangeability requirements of the appropriate IEC component standard where applicable.

NOTE Examples of components are lampholders, switches, transformers, ballasts, flexible cables and cords and plugs.

**0.5.4** Compliance with this document can only be ensured if protective shields of identical specification are used.

## **0.6 List of parts of IEC 60598-2**

- Part 2-1 Fixed general purpose luminaires
- Part 2-2 Recessed luminaires
- Part 2-3 Luminaires for road and street lighting
- Part 2-4 Portable general purpose luminaires
- Part 2-5 Floodlights
- Part 2-6 Luminaires with built-in transformers for tungsten filament lamps<sup>4</sup>
- Part 2-7 Portable luminaires for garden use<sup>5</sup>
- Part 2-8 Handlamps
- Part 2-9 Photo and film luminaires (non-professional)<sup>6</sup>
- Part 2-10 Portable luminaires for children
- Part 2-11 Aquarium luminaires
- Part 2-12 Mains socket-outlet mounted nightlights
- Part 2-13 Ground recessed luminaires
- Part 2-14 Luminaires for cold cathode tubular discharge lamps (neon tubes) and similar equipment
- Part 2-15 Not used at present
- Part 2-16 Not used at present
- Part 2-17 Luminaires for stage lighting, television and film studios (outdoor and indoor)
- Part 2-18 Luminaires for swimming-pools and similar applications
- Part 2-19 Air-handling luminaires (safety requirements)
- Part 2-20 Lighting chains
- Part 2-21 Rope lights
- Part 2-22 Luminaires for emergency lighting
- Part 2-23 Extra-low-voltage lighting systems for filament lamps
- Part 2-24 Luminaires with limited surface temperatures
- Part 2-25 Luminaires for use in clinical areas of hospitals and health care buildings

---

<sup>4</sup> Withdrawn.

<sup>5</sup> Withdrawn.

<sup>6</sup> Withdrawn.



## **0.7 Information for luminaire design in light sources standards**

**0.7.1** In accordance with IEC guidelines, IEC standards are divided into those covering either safety or performance.

**0.7.2** In light source safety standards, "information for luminaire design" is given for the safe operation of light sources; this shall be regarded as normative when testing luminaires in accordance with this document.

**0.7.3** In light source performance standards, "information for luminaire design" is given for the correct performance of light sources; this shall be regarded as informative when testing luminaires in accordance with this document. Testing of light source performance is not required as part of the type test approval for luminaires.

**koniec náhľadu – text ďalej pokračuje v platenej verzii STN**